

Improving the energy efficiency of the lighting system

The main measures to improve the **energy efficiency** of **lighting** are as follows:

- Replacement of **light sources** with new **energy-efficient lamps** while ensuring the established lighting standards;
- Maximum use of natural light during the day and **automatic control** of artificial lighting depending on the level of natural light.
- **Lighting** can be controlled by **infrared sensors** of human presence or movement;
- Use of modern **lighting** fixtures with rational **light** distribution;
- Use of **electronic control equipment** (ballast);
- The use of circuit breakers for **emergency lighting systems** in areas of temporary staff;
- Painting of surfaces of industrial premises and the equipment in light tone for increase of efficiency of use of natural and **artificial lighting**.

You should also pay attention to the following **energy saving measures** for **lighting** installations:

1. Replacement of existing **luminaires** with more **efficient** ones;
2. Replacement of **starting** and **regulating equipment**;
3. Combined lighting;
4. **Automatic lighting control**;
5. Use of **compact fluorescent lamps** (CFLs) for interior lighting;
6. Use of **lighting control systems**.

1. Replacing existing **luminaires** with more **efficient** ones.

The table below shows the possible **energy savings** by replacing less efficient light sources with more efficient ones

Table. 1. Possible **savings of electricity** at

transition to more **efficient light sources**

Light source replacement	Energy savings,%
incandescent lamp* on compact fluorescent lamp	40-60
incandescent lamp* on fluorescent lamp	40-54
incandescent lamp* on mercury discharge lamp	41-47
incandescent lamp* on metal halide lamp	54-65
incandescent lamp* on Sodium Discharge Lamp	57-71
fluorescent lamp on metal halide lamp	20-23
mercury discharge lamp on metal halide lamp	30-40
mercury discharge lamp on Sodium Discharge Lamp	38-50

* When reducing the normalized illumination for **incandescent lamp** by one degree in accordance with the lighting norms.

2. Replacement of **starting and regulating equipment**.

The use of **fluorescent light sources** in the set instead of the standard control gear (ballast), **electromagnetic ballast** with reduced **losses** increases the light output of the kit by $6 \div 26\%$, and **electronic ballast** - by $14 \div 55\%$. equipment.

Table. 2. Coefficient of **electricity losses** in the **starting-regulating equipment**

№	Lamp type	Type of ballast	Coefficient
			losses in the ballast
1	Fluorescent Lamp LB	Normal electromagnetic	1,22
2	Fluorescent Lamp LB	Electromagnetic with reduced losses	1,14
3	Fluorescent Lamp LB	Electronic	1,10
4	Fluorescent Lamp KL	Normal electromagnetic	1,27
5	Fluorescent Lamp KL	Electromagnetic with reduced losses	1,15
6	Fluorescent Lamp KL	Electronic	1,10
7	mercury discharge lamp	Ordinary electromagnetic	1,08
8	mercury discharge lamp	Electronic	1,06
9	Sodium Lamp	Normal electromagnetic	1,10
10	Sodium Lamp	Electronic	1,06

3. Combined lighting

The use of combined (general + localized) lighting instead of general lighting allows you to **save electricity**.

Table. 3. **Energy savings** when using a combined lighting system

Share of auxiliary area from total area of the room,%	Energy savings,%
25	20÷25
50	35÷40
75	55÷65

For rooms larger than 50 m², automatic artificial lighting control devices should be used depending on the natural light of the room. **Automatic control systems (ACS)** allow you to adjust the brightness of the **light source** (LL, CFL) from 100% to 0%. The **automatic control system** must be duplicated by manual lighting control.

4. Automatic lighting control

Energy savings with the introduction of **automatic lighting control** can be estimated using the table. 4.

Table 4. Energy savings during implementation

automatic lighting control

No	The level of complexity of the system	Savings electricity, %
	automatic lighting control	
1	Light level control and automatic switching on and off of lighting system at a critical value of illumination	10÷15
2	Zonal lighting control (switching lighting on and off discretely, depending on from the zonal distribution of natural light)	20÷25
3	Smooth control of power and flux of lamps depending on the distribution natural light	30÷40

Table. 5. **Save electricity** when using different ways to regulate artificial lighting

Number of workers changes	Type of natural lighting in indoor	Method of regulation artificial lighting	Saving electric energy, %
1	Upper	Continuous	36-27
		Stepped	32-13
	Lateral	Continuous	22-7
		Step	12-2
2	Upper	Continuous	31-23
		Step	27-11

Lateral	Continuous	19-6
	Step	10-2

5. Use of CFLs for interior lighting

Economical **compact fluorescent lamps** (integrated - with ballast built into the threaded base) are designed for use in office space. In the table. 6 compares **compact fluorescent lamps** (CFLs) with **incandescent lamps**. The table shows that the use of **CFLs** instead of **LR** at the same luminous flux can significantly reduce **power consumption**. **CFLs** are available with the same base as **incandescent lamps**, which makes it easy to replace **incandescent lamps**.

Table. 6. Comparison of the characteristics of **incandescent lamps**

with **compact fluorescent lamps**

incandescent lamps	CFL	The ratio of light
Power, W	Light flow, lm	return of CFL to LR , relative unit.
25	200	4,3
40	420	5,3
60	710	4,5
75	940	4,7
100	1360	4,3
2x60	1460	5,4

Costs are reduced:

- to replace incandescent lamps 10 times;
- to pay for electricity 5.4 times.

6. Use of [lighting control systems](#)

Significant savings in electricity consumption for lighting can be obtained with the help of a rational **lighting control system**. Such systems enable or disable lighting fixtures under the following conditions:

- depending on the level of natural light in the premises (for example, by photorelay signals);
- when a certain time of day is reached (for example, by timer signals);
- when a person presses the control buttons (for example, entering the entrance, the person presses a button that gives a signal to turn on the lights, the lights are turned off automatically at a specified time interval);
- at input of signals from presence sensors.

Lighting control systems are very common abroad. When implementing them, it should be borne in mind that they complicate lighting networks and in many cases reduce the service life of some types of lamps. For example, each inclusion of a fluorescent lamp reduces its service life by about two hours. The service life of incandescent lamps with the number of inclusions of about 2500 hours is practically unchanged. With a large number of inclusions of incandescent lamp, you can use a soft

Improving the energy efficiency of the lighting system

Published on PATRIOT-NRG International portal for energy saving (<https://www.patriot-nrg.com>)

start system that prevents current surges in the filament of the lamp when it is turned on, when the spiral material has a low temperature and its electrical resistance is low.

According to PMKEU "[PATRIOT](#)"

Source URL: <https://www.patriot-nrg.com/en/content/improving-energy-efficiency-lighting-system-0>